



Product Description

HID-PrimaVision Mini Built-in for CDM

Miniature, lightweight, one-piece electronic gear for 20W and 35W CDM Mini and 35W CDM lamps

Benefits

- Miniaturisation for stylish luminaire design and retrofit halogen replacement
- Minimal lamp power tolerance gives optimal lamp performance
- Robust ignition thanks to resonant ignition
- Reduces colour differences between lamps and reduces initial lumen spread
- Silent operation
- Performance is independent of mains voltage
- Easy luminaire design-in
- Simple installation and cabling with push-in contacts
- High quality means in trouble-free installation


Features

- Available as Standard (*S*) version for use in a luminaire
- 20W LPF also available as PCB (*P*) version for use in a luminaire
- 20W available as High Power Factor (HPF) and Low Power Factor (LPF)
- Smallest gear available
- Minimal lamp power spread
- Microprocessor controlled
- Resonant ignition voltage <1.5kV (20W) and <2.0kV (35W)
- Lamp end-of-life detection
- High T_{ambient} and T_{case} temperatures
- Long lifetime of 40,000 hours
- Push-in contacts
- High quality (< 500 ppm)
- High standard of quality thanks to excellence in development and manufacturing processes

Application

- Accent and decorative lighting for shops, public spaces, lobbies and offices
- Suitable for indoor use only

Related products



Compare table

Order code	Full product name
913700665966	HID-PV m 50 /S CDM LPF 220-240V 50/60Hz
913700601566	HID-PV m PGJ5 20 /P CDM LPF 220-240V
913700601466	HID-PV m PGJ5 20 /S CDM LPF 220-240V
913700646166	HID-PV m 20 /S CDM HPF 220-240V 50/60Hz
913700653666	HID-PV m 35 /S CDM HPF 220-240V 50/60Hz
913700656766	HID-PV m PGJ5 20 /S CDM HPF 220-240V



© 2011 Koninklijke Philips Electronics N.V.
All rights reserved.

Specifications are subject to change without notice. Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.

www.philips.com/lighting

2011, August 18
data subject to change